



MODEL	OUTPUT DC		
	VOLTAGE(V)	CURRENT(mA)	VA
AD-0902000DK	9	2000	18
AD-1021500DK	12	1500	18
AD-1201600DK	12	1600	19.2
AD-1202000DK	12	2000	24
AD-1351500DK	13.5	1500	20.25
AD-1501500Dk	15	1500	22.5
AD-1801500DK	18	1500	27
AD-2401000DK	24	1000	24

FOR OUTPUT PLUG TABLE
SEE PAGE 2

Rev		Drawn	Checked	Approved	Date	SMP TECHNOLOGY, INC. AC/DC ADAPTER, DESKTOP POWER SUPPLY, INPUT: 230VAC 50Hz SAFETY: EN60950, 61558 & CE SERIES: EI57-DESKTOP-UK-DC OUTPUT
0	Issued	B.S.	S.M.	S.M.	09/10/08	
TOL. DEC.	.X +/-	.XX +/-	.XXX +/-	ANGLE +/-	UNIT: mm	Pg: 1

STRAIGHT

MALE PLUG STRAIGHT (parallel cord)

	Part Number	D +/-0.1		L+/-0.5	Wire Gauge
	SM1A	ø2.5		11	#22 #24
	SM2A	ø3.5		14	#22 #24

MALE PLUG STRAIGHT (parallel/coaxial cord)

	Part Number	D +/-0.1		L+/-0.5	Wire Gauge
	SM2B	ø3.5		14	#22 #24

FEMALE PLUG STRAIGHT (parallel cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	SF2A	ø3.5	ø1.3	7	#22 #24
	SF2B	ø3.5	ø1.3	9.5	#22 #24
	SF2C	ø3.5	ø1.3	11	#22 #24
	SF2D	ø3.5	ø1.3	14	#22 #24
	SF3A	ø5.0	ø2.1	9.5	#20
	SF3B	ø5.0	ø2.1	11	#20
	SF3C	ø5.0	ø2.1	14	#20
	SF5C	ø5.5	ø2.5	9.5	#18,#20
	SF5B	ø5.5	ø2.5	11	#18,#20
SF5A	ø5.5	ø2.5	14	#18,#20	
SF6A	ø6.5	ø3.0	9.5	#20	
SF6B	ø6.5	ø3.0	11	#20	

FEMALE PLUG STRAIGHT (parallel cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	SF3D	ø5.0	ø2.1	9.5	#22 #24
	SF3E	ø5.5	ø2.1	11	#22 #24
	SF5D	ø5.5	ø2.1	9.5	#22 #24
SF5E	ø5.5	ø2.5	11	#22 #24	

FEMALE PLUG STRAIGHT (parallel cord #20,#22,#24 /Coaxial #22)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	SF5F	ø5.5	ø2.1	9.5	#20,#22,#23
	SF5G	ø5.5	ø2.1	11	#20,#22,#23
	SF5H	ø5.5	ø2.5	9.5	#20,#22,#23
SF5I	ø5.5	ø2.5	11	#20,#22,#23	

FEMALE PLUG STRAIGHT (SPT-1#18 & XTW-A #20 Cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
SF5J	ø5.5	ø2.1	12.5	#18,#20	

FEMALE PLUG STRAIGHT (parallel/coaxial cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	SF5K	ø5.5	ø2.1	9.5	#22 #24
	SF5L	ø5.5	ø2.1	11	#22 #24
	SF5M	ø5.5	ø2.1	14	#22 #24
SF5N	ø5.5	ø2.5	11	#22 #24	

MINI DIN MALE PLUG, STRAIGHT

	Part Number	Pin Configuration
	SMD3	
	SMD4	
	SMD5	
	SMS5	
	SMD6	
	SMD7	

RIGHT ANGLE

FEMALE PLUG RIGHT ANGLE (parallel cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	RF4A	ø5.03	ø1.57	8.2	#22 #24
	RF4B	ø5.03	ø1.57	13.5	#22 #24
	RF3A	ø5.0	ø2.1	9	#22 #24
	RF3B	ø5.0	ø2.1	11	#22 #24
	RF3C	ø5.0	ø2.5	11	#22 #24
	RF5A	ø5.5	ø1.3	11	#22 #24
	RF5B	ø5.5	ø2.1	9.5	#22 #24
	RF5C	ø5.5	ø2.5	9.5	#22 #24
	RF5D	ø5.5	ø2.1	11	#22 #24
RF5E	ø5.5	ø2.5	11	#22 #24	

FEMALE PLUG RIGHT ANGLE (parallel cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	RF2A	ø3.5	ø1.3	9	#22 #24
	RF2B	ø3.5	ø1.3	11	#22 #24
	RF5F	ø5.5	ø2.1	9.5	#22 #24
	RF5G	ø5.5	ø2.1	11	#22 #24
	RF5H	ø5.5	ø2.5	9.5	#22 #24
RF5I	ø5.5	ø2.5	11	#22 #24	

FEMALE PLUG RIGHT ANGLE (Coaxial cord)

	Part Number	D +/-0.1	d+/-0.1	L+/-0.5	Wire Gauge
	RF5J	ø5.5	ø2.1	9.5	#22 #24
	RF5K	ø5.5	ø2.1	11	#22 #24
	RF5L	ø5.5	ø2.5	9.5	#22 #24
RF5M	ø5.5	ø2.5	11	#22 #24	

MALE/FEMALE PLUG RIGHT ANGLE (Parallel cord)

	Part Number	D +/-0.1		L+/-0.5	Wire Gauge
RM2A	ø3.5		16.5	#22 #24	

MINI DIN MALE PLUG, RIGHT ANGLE

	Part Number	Pin Configuration
	RMD3	
	RMD4	
	RMD5	
	RMS5	
	RMD6	
	RMD7	

OUTPUT PLUG TABLE